

COIL PART NUMBER	RESISTANCE(s)	FUNCTION(s)	TENSION
A-489	15 OHMS	ADVANCE UNIT RELAY BALL GATE RELAY 00-90 UNIT RELAY (MATCH UNIT)	25 Volts
A-1118	3.5 OHMS	BONUS INCREASE RELAY CONTROL BANK DOUBLE BONUS RELAY EXTRA BALL RELAY 1st BALL RELAY GAME OVER RELAY LAST BALL RELAY RESET CONTROL RELAY 2nd,3rd,4th PLAYER RELAY	25 Volts
A-1119	2 OHMS	ROLLOVER RELAY	25 Volts
A-1469	3 OHMS	GENERAL PURPOSE	25 Volts
A-1496	3 OHMS	STEP-UP BALL PLAYER STEP-UP BONUS UNIT STEP-UP PLAYER UNIT STEP-UP REPLAY UNIT BALL RETURN BALL SHOOTER HOLE KICKER KICKING RUBBER KICKING TARGET POP BUMPER 0-9 UNIT	25 Volts
A-4893	2 OHMS	BALL KICKER POP BUMPER UP KICKER	25 Volts
A-5141	1 OHM / 8 OHMS	FLIPPER FLIPPER	25 Volts
A-5143	3 OHMS	BELL BELL KNOCKER KNOCKER	25 Volts
A-5193	5 OHMS	SCORING	25 Volts
A-5194	4.5 OHMS	STEP-UP BONUS UNIT STEP-UP COIN UNIT STEP-UP CORNER UNIT STEP-UP PLAYER UNIT STEP-UP REPLAY UNIT FLIPPER GONG HOLE KICKER HOLE KICKING RUBBER TARGET KICKING TARGET KNOCKER KNOCKER POP BUMPER POP BALL PLAYER RESET COIN UNIT CORNER UNIT RESET SUBTRACT BONUS UNIT REPLAY UNIT SUBTRACT REPLAY UNIT UP KICKER	25 Volts

COIL PART NUMBER	RESISTANCE(s)	FUNCTIONS	TENSION
A-5195	12 OHMS	BALL RELEASE	25 Volts
		CHIME	
		CONTACT KICKER	
		KNOCKER	
		OUTHOLE	
A-5196	13 OHMS	CONTROL BANK RESET	110 Volts
		TARGET BANK RESET	
A-5197	??	ROTO UNIT ROTO UNIT	25 Volts
A-5294	??	2 COINS PER PLAY RELAY	110 Volts
A-5662	7,5 OHMS	LAST BALL RELAY	25 Volts
		LOCK RELAY	
		RESET CONTROL RELAY	
A-6698	10,5 OHMS	2 COINS, 3 PLAYS RELAY	25 Volts
A-7677	0,5 OHM	COIN LOCKOUT	25 Volts
A-7800	1 OHM	CONTROL BANK RESET	25 Volts
A-7833	390 OHMS	GENERAL PURPOSE	110 Volts
A-9154	6,5 OHMS	SCORING UNIT	25 Volts
A-9479	21,5 OHMS	SEQUENCE BANK RESET	110 Volts
		TARGET RESET BANK (50 HZ)	
A-9731	??	COIN CHUTE RELAY	110 Volts
A-9733	2 OHMS	SERIES RELAY	25 Volts
A-9735	14 OHMS	STEP-UP BONUS UNIT RELAY	25 Volts
		STEP-UP PLAYER UNIT RELAY	
		STEP-UP REPLAY UNIT	
		BALL RETURN RELAY	
		BALL SHOOTER RELAY	
		BONUS SCORE RELAY	
		CONTROL BANK RESET	
		HOLE VALUE RELAY	
		LAST BALL RELAY	
		PLAYERS RESET RELAY	
		POP BUMPER RELAY	
		RESET CONTROL RELAY	
		SCORE CONTROL RELAY	
		SPIN TARGET RELAY	
		START RELAY	
10-100-500-1000 POINTS RELAY			
A-9736	25,5 OHMS	ALTERNATING RELAY	25 Volts
		COIN LOCKOUT	
		EXTRA BALL RELAY	
		1st BALL RELAY	
		GAME OVER RELAY	
		HOLD RELAY	

COIL PART NUMBER	RESISTANCE(s)	FUNCTION(s)	TENSION
A-9738	30 OHMS	ALTERNATING RELAY	25 Volts
		115 VOLT RELAY	
		EXTRA BALL RELAY	
		HOLD RELAY	
		100,000 POINTS RELAY	
		30 VOLTS HOLD RELAY	
		TILT HOLD RELAY	
A-9740	20 OHMS	"A","B","C", RELAY	25 Volts
		STEP-UP REPLAY UNIT	
		BONUS BOOSTER RELAY	
		BONUS SCORE CONTROL	
		1st BALL RELAY	
		1st,2nd,3rd, CHUTE RELAY	
		GAME OVER RELAY	
		REPLAY BUTTON RELAY	
		SEQUENCE COMPLETED RELAY	
		START RELAY	
		3rd CHUTE DELAY RELAY	
VARI - TARGET RESET			
A-9741	??	REPLAY BUTTON RELAY	110 Volts
		2 PLAY RELAY	
A-9742	11 OHMS	TILT RELAY	25 Volts
A-9746	2 OHMS	DOUBLE BONUS RELAY	25 Volts
		SERIES RELAY	
A-12092	??	CHIME	25 Volts
A-15259	7.5 OHMS	SCORING UNIT	25 Volts
A-15359	0.5 OHM	DOUBLE BONUS CONTROL RELAY	25 Volts
		EXTRA BONUS RELAY	
A-15555	9.5 OHMS	TARGET RESET BANK (60 HZ)	110 Volts
A-16570	15.5 OHMS	KICKOUT HOLE	25 Volts
		OUTHOLE	
A-16890	230 OHMS	ALTERNATING RELAY	25 Volts
		COIN LOCKOUT	
		EXTRA BALL RELAY	
		GAME OVER RELAY	
		TILT RELAY	
A-17564	156 OHMS	VARI-TARGET	25 Volts
A-17875	3 OHMS / 40 OHMS	FLIPPER	25 Volts
A-17876	24 OHMS 24 OHMS	CHIME	25 Volts
A-17891	3,5 OHMS 3.5 OHMS	ROTO UNIT ROTO UNIT	25 Volts
		TARGET BANK RESET (5 pos.)	
A-18102	9 OHMS	TARGET RESET BANK (7 pos.)	25 Volts

COIL PART NUMBER	COIL RESISTANCE(s)	FUNCTION(s)	TENSION
A-18318	7 OHMS	BANK TARGET RESET (4 pos.)	25 Volts
A-18642	58 OHMS	MEMORY / DROP TARGET TRIP	25 Volts
A-19217	25.5 OHMS	DROP TARGET TRIP (Pinball Pool)	25 Volts
A-19300	8 OHMS	BALL KICKER	25 Volts
A-19508	35 OHMS	DROP TARGET TRIP	25 Volts
A-20095	2 OHMS / 35 OHMS	SUPER FLIPPER	25 Volts
A-20558	156 OHMS	GATE GATE	25 Volts
A-21741	2,5 OHMS 2.5 OHMS	UP KICKER	25 Volts
A-24161	2 OHMS / 40 OHMS	INTERMEDIATE FLIPPER	25 Volts
A-25959	4 OHMS / 202 OHMS	FLIPPER (New unit)	25 Volts
A-26450	42 OHMS 42 OHMS	GENERAL PURPOSE	25 Volts
A-26451	66 OHMS 66 OHMS	GENERAL PURPOSE	25 Volts
A-26452	137 OHMS 137 OHMS	DROP TARGET TRIP	25 Volts
A-26646	5 OHMS / 201 OHMS	FLIPPER (New Unit)	25 Volts
A-26649	28,5 OHMS	GENERAL PURPOSE	25 Volts
A-26926	33 OHMS	BANK TARGET RESET	25 Volts
A-27642	9 OHMS / 203 OHMS	FLIPPER (New Unit)	25 Volts
A-27643	11 OHMS / 202 OHMS	FLIPPER (Old unit)	25 Volts
A-27926	65 OHMS	GENERAL PURPOSE	25 Volts